

BL High-Power Series



FEATURES

- Multi-Pulse Input Rectification - Low Harmonic Distortion
- Analog Remote Control - Remote Programming
- Low cost per VA - Cost Savings
- Compact Size - Less rack space

Behlman's BL High-Power Series AC Power Sources supply clean, regulated AC power in a compact design at competitive prices. The BL High-Power Series is available with either single- or three-phase output in a wide range of power from 1 KVA to 20 KVA. Inputs are any worldwide three-phase mains power with some models available with single-phase input.

The BL High-Power Series delivers all the quality features our customers have come to expect from Behlman; clean sine wave output with excellent line and load regulation, high efficiency and low harmonic distortion. A multi-pulse input transformer offers low-input harmonic distortion and high power factor as required by MIL-STD-1399 and European standards. Unique protection circuitry provides for over-temperature protection, short-circuit protection and voltage fold-back during overloads to maintain undistorted waveforms.

Amplitude and Frequency adjustment, line drop compensation, phase angle adjust and output on/off come standard. Units are supplied with analog remote control and available optional RS-232 and IEEE-488 remote control interfaces. Other options include CE mark, Extended Frequency range up to 1000 Hz and Motor Test option which has the capability to soft-start motors, pumps and compressors thereby eliminating the need for high power devices.

Small size, quiet operation and high efficiency make the BL High Power series ideal for industrial products testing, precision avionic test and power conversion, ATE, bulk power and motor generator replacement.

The BL High Power series is easily modified to meet your requirements.

INPUT

Multi-pulse input transformer for low input current THD in the following configurations.

VOLTAGE

C-1	120/208 VAC	3 Phase
C-2	220/380 VAC	3 Phase
C-3	277/480 VAC	3 Phase
C-4	200 VAC, Delta	3 Phase
C-5	346/600 VAC	3 Phase
C-6	230/400 VAC	3 Phase
C-7	240/415 VAC	3 Phase
C-8	115/230 VAC	1 Phase (Note 1 & 2)
C-9	230 VAC	1 Phase (Note 3)
C-10	480 VAC	1 Phase (Note 3)

Contact factory for other input voltages

Note

1. C-8 for Model BL3X350 in same 7"H chassis
 2. C-8 for Models BL3100, BL3200 & BL3300 requires 7"H chassis in place of 3.5"H
 3. C-9 & C-10 for Models BL4500, BL5000 & BL5100 includes option 21-00 Cabinet
- See mechanical specification 4

Frequency

47 - 440 Hz

TABLE 1: BL HIGH-POWER SERIES MODEL SELECTION

Model Number	Power W	Output Volts AC	Current A	Mechanical Specifications
BL3100	3 KVA	0-135, 1 Phase	22 Amps	1
BL5100	5 KVA	0-135, 1 Phase	37 Amps	2
BL7000	7 KVA	0-135, 1 Phase	52 Amps	2
BL3200	3 KVA	0-270, 1 Phase	11 Amps	1
BL4500	4.5 KVA	0-270, 1 Phase	17 Amps	2
BL6000	6 KVA	0-270, 1 Phase	22 Amps	2
BL9200	9 KVA	0-270, 1 Phase	33 Amps	2
BL12000	12 KVA	0-270, 1 Phase	44 Amps	3
BL3X350	1 KVA	0-135, L - N, 3 Phase	2.6 Amps/ph	4
BL3300	3 KVA	0-135, L - N, 3 Phase	7.5 Amps/ph	1
BL5000	5 KVA	0-135, L - N, 3 Phase	12.5 Amps/ph	2
BL10000	10 KVA	0-135, L - N, 3 Phase	25 Amps/ph	2
BL15000	15 KVA	0-135, L - N, 3 Phase	37 Amps/ph	3
BL20000	20 KVA	0-135, L - N, 3 Phase	50 Amps/ph	3

Contact factory for other output voltages

MECHANICAL SPECIFICATIONS

1. (2) 19" (48.3 cm) rack-mount chassis 7" H and 3.5" H x 22" D (17.8 cm and 8.9 cm H x 55.9 cm D) ... 150 lbs (68.1 kgs)
2. (2) 19" (48.36 cm) rack-mount chassis 7" H and 8.75" H x 22" D (17.8 cm and 22.2 cm H x 55.9 cm D) ... 250 lbs (113.5 kgs)
3. High-strength cabinet with casters 28.3" H x 31.6" D x 22.1" W (71.9 cm H x 80.3 cm D x 55.6 cm W) ... 425 lbs (193.0 kgs)
4. (1) 19" (48.3 cm) rack-mount chassis 7" H and 22" D (17.8 cm x 55.9 mm D) ... 65 lbs (29.5 kgs) (C-8 Input Only)

OUTPUT

Power	See Table 1
Voltage	See Table 1
Resolution	1 V
Accuracy	+/- 2 % of full scale
Frequency	45-500 Hz (Option E: 45-1000 Hz)
Resolution	1 Hz
Accuracy	+/- 2 Hz
Current	See Table 1
Resolution	0.1 Amp, +/- 1 digit
Accuracy	+/- 2 % of full scale
Crest Factor	3:1
Power Factor	100% of rated output into any power factor load
Distortion	3% THD Typical
Line Regulation	0.1% for +/- 10% line change
Load Regulation	0.7% no load to full load
Efficiency	80% typical

PROTECTIVE CIRCUITS

Input	Fast-acting main circuit breaker
Constant Current	Overload automatically causes voltage fold back to provide maximum current without distorting output waveform
Short Circuit	Short circuit electronically latches output open to protect load...power restored by cycling circuit breaker
Thermal	Internal temperature sensor prevents heat damage

CONTROLS / INDICATORS

Power On/Off	Circuit breaker
Meters	Three (3) DMM: True RMS Volts, True RMS Amps, Frequency
Voltage Adjust	Ten-turn potentiometer to adjust voltage
Frequency Adjust	Ten-turn potentiometer to adjust frequency
Phase select	Three-position switch for phase A, B or C *
Line Drop	Allows for front panel adjustment of output to compensate for voltage drop over long distance
Phase angle adjust	Allows for front panel adjustment of phase angle A-B and B-C *
Output	Toggle switch
Indicators	Power On, Constant Current, Overtemp, Overload Latch
External Synch	Synchronizes AC output with external input
Remote Control	0-10 VDC programming for voltage and frequency...contact closure for output on/off...external synch

ENVIRONMENTAL / CONNECTIONS

Operating Temp	32° F to 131° F (0-55° C)
Humidity	0-95% RH non-condensing
Input Connections	Barrier strip on rear
Output Connections	Barrier strip on rear
Remote Control	DB-9 connector

OPTIONS

CE	CE Mark
E	Extended frequency range, 45-1000 Hz
I	IEEE-488 Interface
IR	RS232 Interface
L	Locking pot
MT	Motor test (not available on BL12000, BL15000 and BL20000)
R	Ruggedized for use in areas with shock and vibration
S1	Slides for Mechanical Specifications 4
S3	Slides for Mechanical Specifications 1
S10	Slides for Mechanical Specifications 2
T3D	0-135 & 0-270 VAC L-N on BL3300 (add 3.5" chassis)
T5	0-300 VAC L-N on BL5000 (add 7" chassis)
T5D	0-135 & 0-300 VAC L-N on BL5000 (add 7" chassis)
T10	0-300 VAC L-N on BL10000 (add 7" chassis)
T10D	0-135 & 0-300 VAC L-N on BL10000 (add 7" chassis)
T15	0-300 VAC L-N on BL15000
T20	0-300 VAC L-N on BL20000
21-00	Cabinet with casters

* (Three-phase units only)

ORDERING INFORMATION

BL X X 0 0 C - X - X



